

# Lux Meter- EQ 1301

Cost effective pocket size lux meter which measures lux intensity both in terms of Foot candle ( Fc ) or lux ( lx ). Has the feature of low battery indication and peak hold.



Model : EQ-1301

## Features

- ▶ 3½ digital LCD display
- ▶ Max Hold and Data Hold
- ▶ Auto Power Off
- ▶ Low battery indication
- ▶ User selectable Fc/Lux

## Specifications

<b>Display</b>	<b>LCD 1999 Counts</b>
<b>Measuring Range</b>	<b>0 to 50,000 lux</b>
<b>Accuracy</b>	<b>±5% + 10d (&lt; 10,000 lux)</b>
<b>Repeatability</b>	<b>± 2%</b>
<b>Measuring Rate</b>	<b>1.5 times / sec</b>
<b>Auto Power off</b>	<b>After 15 min. of Inactivity</b>
<b>Photo Detector</b>	<b>Silicon photo diode with Iiter</b>
<b>Dimension</b>	<b>188 × 64.5 × 24.5 (H × W × D)</b>
<b>Storage Temperature</b>	<b>-10 to 60°C at &lt; 80% RH</b>
<b>Power Supply</b>	<b>1 × 1.2 V Battery</b>
<b>Weight</b>	<b>160gms</b>



## Valli Aqua and Process Instruments

1/231A, Pananchalai street,

TM Near Maduravoyal bypass bridge, Adayalampattu,  
Chennai-600095, Tamil Nadu, India.

Mob.no- +91 9840752690

mail id- enquiry@vapinstruments.in&kvgiri\_59@yahoo.in

[www.valliaquaprocess.com](http://www.valliaquaprocess.com) & [www.vapinstruments.in](http://www.vapinstruments.in)